

15502 Repeater

OVERVIEW

The NotifEye™ Repeater extends the normal operating range of a wireless network. It is used to bridge the gap between NotifEye sensors and the NotifEye gateway when the distance between them is too long for a direct connection. Data coming from the sensor is delivered to the repeater and forwarded to the gateway at a rate of 6 messages per minute.

FEATURES	BENEFITS
<ul style="list-style-type: none"> • Extends coverage area (range) of your network (250-300 ft) • AC powered • Supports up to 100 sensors • Stores up to 30,000 messages if gateway is unavailable • LED status/activity light 	<ul style="list-style-type: none"> • Allows for greater distance between sensors and gateways • No batteries required • Reduces congestion from multi-sensor networks • Data is stored in the event of gateway power loss • Four visual alerts to identify network connectivity <ul style="list-style-type: none"> - Flashing red & green: Looking for a gateway to connect to - Solid red: No gateway found - Solid green: Has connected to a gateway - Flashing green: Sensor data is intercepted and relayed
<p>Specifications:</p> <ul style="list-style-type: none"> • Dimensions: (L x W x H) 3.09" x 2.085" x 1.417" (78 mm x 53 mm x 36 mm) • Antenna: 7.25" (184 mm) with SMA connector • Communication: 900 MHz • Power: AC • 1-year warranty 	

